

Product Line  
**FORTIRACK**

Type  
**RM-FR-T14**  
**RM-FR-T14i**

Supported Models **FORTIGATE 40F**  
**FORTIADC 60F**

DIMENSIONS 1U  
COLOR RAL 9003 White  
PACKING DIMENSIONS 80 x 520 x 270 mm  
3.14 x 20.47 x 10.63 in  
PRODUCT DIMENSIONS 44 x 482 x 217 mm  
(height x width x depth) 1.73 x 18.98 x 8.54 in



## MOUNTING INSTRUCTIONS

Depending on your FortiGate model:

1. Option 1: place your FortiGate on the rack & fix the FortiGate with the 2 countersunk bolts from the bottom and tighten them lightly.  
Option 2: remove the original bolt from one side of the appliance, place your FortiGate on the rack & use the provided bolt to fix the FortiGate.
2. Place the power supply on the rack and tie it down with the 2 zip ties, tie the excess length of the power cable down with the 3rd zip tie.
3. Connect the cables from your FortiGate to the connectors.
4. Optional: use two zip ties to hold the cables together.
5. Place your FortiRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

## PACKAGE CONTENTS

Qty	Description
1	FortiRack + RJ45 couplers
3	Bolts M3x6mm
5	Zip ties
7	Cables - 0.5 meter



**Consider the environment,  
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or [sales@rackmount.it](mailto:sales@rackmount.it).

Industrial version is supplied with shielded couplers and cables

Revision 8 - 25-06-2021

EMEA Office  
Nonneveld 27  
4811 HN Breda  
The Netherlands  
T +31 76 200 37 40  
E [sales@rackmount.it](mailto:sales@rackmount.it)  
[WWW.RACKMOUNT.IT](http://WWW.RACKMOUNT.IT)

US Office  
9201 Metric Blvd - Unit A  
Austin - TX 78758  
United States  
T +1 512 521 03 33  
E [sales-us@rackmount.it](mailto:sales-us@rackmount.it)

**RACKMOUNT.IT**