


4-Port Component Video + Stereo Audio over Cat5/Cat6 Extender Splitter, Box-Style Transmitter, Up to 700-ft.

MODEL NUMBER: **B136-004**



Description

Tripp Lite's B136-004 takes a single Component Video and Stereo Audio signal and splits it to five(1 local, 4 remote). When used in conjunction with a [B136-100](#) remote unit, you can transmit a Component Video(YPbPr) and Stereo Audio signal from any DVD player, PS3, or Cable/Satellite device to up to four displays over a single CAT5, CAT5E, or CAT6 cable. A 1080i(60Hz) Component Video and Stereo Audio signal can be extended up to 300 ft. when using 24Awg, Solid Wire UTP cable(Tripp Lite N202-Series); or, up to 400 ft. when using Zero-Skew UTP cable(Tripp Lite [P524-01K](#)). A 480p(60Hz) Component Video and Stereo Audio signal can be extended up to 500 ft. when using 24Awg, Solid Wire UTP cable(Tripp Lite N202-Series); or, up to 700 ft. when using Zero-Skew UTP cable(Tripp Lite [P524-01K](#)). The number of displays can be increased to up to 13(1 local, 12 remote) by daisy chaining 3 B136-004 units together. Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases.

Features

- Splits a single Component Video and Stereo Audio signal into five(1 local, 4 remote)
- Features an extra set of Component Video and Stereo Audio connectors for an optional local display
- Works in conjunction with a [B136-100](#) remote unit
- A 1080i(60Hz) Component Video and Stereo Audio signal can be extended up to 300 ft. when using 24Awg, Solid Wire UTP cable(Tripp Lite N202-Series); or, up to 400 ft. when using Zero-Skew UTP cable(Tripp Lite [P524-01K](#))
- A 480p(60Hz) Component Video and Stereo Audio signal can be extended up to 500 ft. when using 24Awg, Solid Wire UTP cable(Tripp Lite N202-Series); or, up to 700 ft. when using Zero-Skew UTP cable(Tripp Lite [P524-01K](#))
- Connect up to 13 displays(1 local, 12 remote) by cascading 3 B136-004 units together
- Includes a 1 ft. Component Video + Stereo Audio daisychain cable
- Up to 3 B136-004 units can be mounted in 1U of rack space when using a [B132-004-RB](#) Extender/Splitter 19 in. rackmount bracket
- Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases

Highlights

- Splits a single Component Video and Stereo Audio signal into five(1 local, 4 remote)
- Extends a 1080i(60Hz) Component Video and Stereo Audio signal up to 300 ft. when using 24Awg, Solid Wire UTP cable(Tripp Lite N202-Series); or, up to 400 ft. when using Zero-Skew UTP cable(Tripp Lite [P524-01K](#))
- Connect up to 13 displays(1 local, 12 remote) by daisy chaining 3 B136-004 units together
- Compliant with the Federal Trade Agreements Act(TAA) for GSA Schedule purchases

System Requirements

- For international use, the [B110-INT](#) power supply can be purchased separately; it features plugs for the UK, Europe, and Australia

Package Includes

- B136-004 4-Port Component Video + Stereo Audio Extender/Splitter
- External Power Supply with NEMA 1-15P Plug (Input: 100-240V, 50/60Hz, 0.5A; Output: 5V, 2A, 5 ft.)
- 1 ft. Component Video + Stereo Audio Source / Daisychain cable
- Owner's Manual



Specifications

| OVERVIEW | |
|-----------------------------------|---|
| AC Adapter | Input: 100-240V, 50/60Hz, 0.5A; Output: 5V, 2A, 5 ft. |
| PHYSICAL | |
| Optional Mounting Accessory Notes | Up to 3 B136-004 units can be mounted in 1U of rack space when using a B132-004-RB Extender/Splitter 19 in. rackmount bracket |
| Unit Dimensions (hwd / in.) | 1.1 x 5 x 4 |
| Unit Dimensions (hwd / cm) | 2.79 x 12.7 x 10.16 |
| Unit Weight (lbs.) | 1.1 |
| Unit Weight (kg) | 0.50 |
| Included Mounting Accessories | Yes |
| Color | Black |
| COMMUNICATIONS | |
| Max 1024 x 768 Range (ft) | 700 |
| Max 480P Range (ft) | 700 |
| Max 1440 x 900 Range (ft) | 400 |
| Max 1080i Range (ft) | 400 |
| Max 480i Range (ft) | 700 |
| Max 640 x 480 Range (ft) | 700 |
| Max 800 x 600 Range (ft) | 700 |
| Max 1600 x 1200 Range (ft) | 400 |
| Max 720P Range (ft) | 400 |
| CONNECTIONS | |
| Ports | 4 |
| Side A - Connector 1 | (5) RCA (FEMALE) |
| Side A - Connector 2 | (5) RCA (FEMALE) |
| Side B - Connector 1 | (4) RJ45 (FEMALE) |
| WARRANTY | |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| | |
|-------------------------------------|-------------------------|
| Product Warranty Period (Worldwide) | 1-year limited warranty |
|-------------------------------------|-------------------------|

© 2016 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.

Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<http://www.tripplite.com/products/product-certification-agencies>