



Flush Mount Desktop Power Outlet

Rotating Opening, Four Power Outlets, Two USB-A Charging Ports, 1.5 m (5 ft.)

Power Cord, Black

Part No.: [164849](#)

EAN-13: 0766623164849 | UPC: 766623164849

Flush Mount Desktop Power Outlet for concealable power

The Manhattan Flush Mount Desktop Power Outlet is a low-profile charging solution you can easily install in the receptacle cutout of a conference room table, office desk, workbench, sofa side or other surface. Its rotatable panel lets charge devices when needed and otherwise keep the outlet closed for a clean, discreet look. When open, it offers four AC power outlets to connect notebooks, printers, monitors, projectors and more while two USB-A ports can charge mobile devices such as phones or tablets. The Flush Mount Desktop Power Outlet makes it so you won't have to crawl under the desk to find a power strip again.

Features:

- Flush mount charging station with four power sockets and two USB-A charging ports
- Two USB-A charging ports with LED and output up to 2.1 A / 5 V DC (max.)
- Rotatable charging panel that can be hidden when not in-use
- Ideal for installation into an office desk, conference room table, workbench or other surface
- Overload, overcurrent and overheating protection
- Built-in cable management for a clutter-free appearance
- Durable, high-quality aluminum alloy material
- Three-year warranty

Specifications:

Standards and Certifications

- FCC

Connections

- Four AC power outlets (NEMA 5-5)
- Two USB-A charging ports (2.1 A / 5 V DC max.)

Input Characteristics

- AC rated voltage: 100 - 240 V
- Frequency range: 50 - 60 Hz

Physical

- Housing dimensions: 262 x 110 x 104 mm (10.32 x 4.33 x 4.09 in.)
- Cutout dimensions for installation: 229 x 103 mm (9.02 x 4.06 in.)
- Power cable length: 1.5 m (5 ft.)
- Weight: 1 kg (2.2 lbs.)

Operating Environment

- Operation temperature: 0 - 50°C (32 - 122°F)
- Storage temperature: -10 - 70°C (14 - 158°F)
- Humidity (noncondensing): 5 - 90% RH

Package Contents

- Flush Mount Desktop Power Outlet
- Two mounting screws
- Instructions



