#### **Datasheet**

# HP LaserJet M209dw Printer

Fast, reliable performance. Exceptional value.

Reliable, high-performance black-and-white two-sided printing in an award-winning compact design.<sup>2</sup>

Increase productivity with this highperformance black-and-white printer in an award-winning compact design.<sup>2</sup> Experience the fastest two-sided printing in class<sup>6</sup> and reliable Wi-Fi with self-reset,<sup>7, 11</sup> plus simplified setup and time-saving features with the HP app.<sup>1,3</sup>



This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

**Print Speed:** Letter: Up to 30 ppm; First Page Out: As fast as 6.9 sec

**Print Resolution:** Black (best): Up to 600 x 600 dpi **Standard Connectivity:** 1 Hi-Speed USB 2.0; 1 Fast Ethernet 10/100Base-TX; 1 Dual-band (2.4/5.0GHz) Wireless 802.11b/g/n with Bluetooth® Low Energy

Mobile Printing Capability: Apple AirPrint™; HP Smart App; Mopria™

Certified; Wi-Fi® Direct printing **Duty cycle:** Monthly (letter): Up to 20,000

Paper Handling: 150-sheet input tray; 100-sheet output tray















#### Built for fast and reliable printing

- Deliver multipage documents in a flash with the fastest two-sided printing in class.<sup>6</sup>
- Rely on consistent, high-quality prints page after page. Get the quality you expect from an industry leader.
- Get better range and faster, more reliable connections using dual-band Wi-Fi™ with self-reset.<sup>4</sup>
- Easily share resources access and print with wireless and Ethernet networking.<sup>6</sup>
- Easily handle high-volume print jobs and reload paper less often with a 150-sheet capacity paper tray.

#### Award-winning design to fit your workspace<sup>2</sup>

- Small in size but big in performance, an impressive combination of advanced power and award-winning design.<sup>2</sup>
- Save space and reduce clutter with a modern sleek design that fits your workspace.
- You can fit this LaserJet almost anywhere. Get projects done quickly with this highperformance compact printer.

### Easy to set up, easy to use

- Get started fast with easy setup guidance from the HP app.<sup>1</sup> Quickly setup and get back to husiness
- Get time-saving Shortcuts, plus access and print documents and images from your mobile devices, with the easiest-to-use HP app.<sup>8,11</sup>
- $\bullet \hspace{0.1in}$  Easily connect your printer to your computer with the built-in USB port.
- Easily manage tasks with smart-guided buttons and lighting for an intuitive experience buttons appear only when needed.

## HP LaserJet M209dw Printer Technical specifications

| Functions  | Print   |
|--|---|
| Print speed black <sup>11</sup> , <sup>9</sup> , <sup>10</sup> | First page out: As fast as 6.9 sec; Letter: Up to 30 ppm; <b>2-sided Letter:</b> Up to 19 ipm; <b>Print speed (Landscape, A5)</b> : Up to 29 ppm  |
| Print resolution   | Black (best): Up to 600 x 600 dpi   |
| Print technology   | Laser   |
| Print cartridges number  | 1 (black)   |
| Standard print languages                                       | PCLmS; URF; PWG   |
| Printer smart software features <sup>2,3</sup>                 | Automatic duplex printing, HP Auto-On/Auto-Off <sup>1</sup> , HP Smart App <sup>2</sup>   |
| Printer management   | HP Printer Assistant (UDC); HP Device Toolbox   |
| Standard connectivity  | 1 Gigabit Ethernet 10/100/1000 Base-TX network; 1 Hi-Speed USB 2.0 (device); Wireless 802.11b/g/n, Dual band 2.4GHz/5GHz  |
| Network capabilities   | 1 Ethernet 10/100Base-TX; 1 built-in Wi-Fi 802.11b/g/n  |
| Wireless capability  | 1 built-in Wi-Fi 802.11b/g/n  |
| Mobile printing capability <sup>8</sup>                        | Apple AirPrint™; HP Smart App; Mopria™ Certified; Wi-Fi® Direct printing  |
| Memory   | Standard: 64 MB; Maximum: 64 MB   |
| Processor speed  | 500 MHz   |
| Hard disk  | None  |
| Duty cycle <sup>12</sup>                                       | Monthly, letter: Up to 20,000; Monthly, A4: Up to 20,000  |
| Recommended monthly page volume <sup>13</sup>                  | 200 to 2,000  |
| Paper handling   | Input Capacities: Up to 150 sheets Up to 10 envelopes Output Capacities: Up to 100 sheets; Up to 10 envelopes Duplex Options: Automatic (standard) Envelope feeder: Yes, 10 Standard paper trays: 1 |
| Media types supported  | Paper (laser, plain, rough, vellum), envelopes, labels, cardstock, postcard   |
| Media weight supported   | 16 to 43 lb   |
| Media sizes supported  | Letter, legal, executive, envelopes   |
| Media Sizes Custom   | 4 x 6 to 8.5 x 14 in  |
| Product dimensions   | <b>W x d x h:</b> 13.98 x 11 x 8.07 in / 355 x 279.5 x 205 mm; <b>Maximum:</b> 13.98 x 16.80 x 10.43 / 355 x 426.5 x 265 mm   |
| Product weight   | 12.35 lb / 5.6 kg   |
| What's in the box <sup>1</sup>                                 | 6GW62F HP Laser Jet Pro M209dw Printer; HP Black Laser Jet Toner<br>Cartridge(~700 pages); Dust Cover; Reference Guide, Setup Poster, Warranty<br>Guide & Flyer in some countries; Power cord       |

| Page yield (set-up/inbox<br>cartridges) <sup>7</sup> | M209, M211: In box cartridge yields ~700 black pages based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see: http://www.hp.com/go/toneryield. Pages may vary based on customer printing conditions and usage. M208, M207: In box cartridge yields ~1150 black pages based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see: http://www.hp.com/go/toneryield. Pages may vary based on customer printing conditions and usage. |
|--|--|
| Replacement supplies <sup>6</sup>                    | HP 134A Black LaserJet Toner Cartridge, W1340A (~1100), HP<br>134X Black LaserJet Toner Cartridge, W1340X (~2400)  |
| Supplies   | W1340A HP 134A Black Original LaserJet Toner Cartridge ; W1340X HP 134X<br>High Yield Black Original LaserJet Toner Cartridge  |
| Warranty features                                    | One-year limited warranty  |
| Ecolabels  | ENERGY STAR® certified   |
| Energy star certified                                | Yes  |
| Blue Angel Compliance                                | Yes, Blue Angel DE-UZ 219—only ensured when using Original HP supplies   |
| Sustainable impact specifications                    | Mercury free   |
| Control panel  | Button LED   |
| Software included                                    | Downloadable Software from hp.com or 123.hp.com #CD include HP Software Installer, Uninstaller, printer driver and other essential tools.  |
| Compatible operating systems <sup>14</sup>           | Windows 11; Windows 10; Windows 8; Windows 8.1; macOS 10.14 Mojave; macOS 10.15 Catalina; macOS 11 Big Sur; macOS 12 Monterey; macOS 15 Sequoia; Linux   |
| Compatible network operating systems                 | Windows 11; Windows Server; macOS 15 Sequoia; Linux  |
| Minimum system requirements                          | PC: Microsoft® Windows® 10, 8.1, 8, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer; Mac. Apple® macOS High Sierra (v10.13) macOS Mojave (v10.14) macOS Catalina (v10.15) macOS Big Sur (v11); 2 GB HD; Internet required  |
| Power , <sup>4</sup>                                 | Power supply type: Internal; Power requirements: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz, 4.6 A; Power consumption: 420 watts cative printing), 2.0 watts (ready), 0.5 watts (sleep), 0.5 watts (latu of/ff/Wake on USB, enabled at shipment), 0.04 watts (Auto-off/Manual-on), 0.04 (Manual Off); Typical electricity consumption (TEC) number <sup>4</sup> : 0.224 kWh/Week (Energy Star)  |
| Acoustics <sup>15</sup>                              | Acoustic power emissions: 6.7 B(A)   |
| Operating environment                                | Operating temperature range: $59$ to $90.5^\circ$ F / $15$ to $32.5^\circ$ C; Recommended operating temperature: $63.5$ to $77^\circ$ F / $17.5$ to $25^\circ$ C; Storage temperature range: $-4$ to $140^\circ$ F / $-20$ to $60^\circ$ C; Non-operating humidity range: $10$ to $90\%$ RH; Operating humidity range: $10$ to $80\%$ RH; Recommended humidity operating range: $30$ to $70\%$ RH  |
| HP Service and Support options                       | U6M41E - HP 2y Onsite Exchange LJ M SVC; U6M42E - HP 3y Onsite Exchange LJ M SVC; U6M42E - HP 3y Onsite Exchange LJ M SVC; UG220E - HP 2y NBD Advance Exchange LJ M SVC; UG221E - HP 2y NBD Advance Exchange LJ M SVC; UG221E - HP 3y NBD Advance Exchange LJ M SVC; UG22EE - HP 4y NBD Advance Exchange LJ M SVC  |
| Security management                                  | Secure Boot, Secure Firmware Integrity, Runtime Code Integrity, password protected EWS, secure browsing via SSL/TLS 1.0, TLS 1.1, TLS 1.2; TLS 1.0/1.1 disabled by default; Update to OpenSSL version 1.1.1; enable/disable Network ports; SNMPv1, SNMPv2, and SNMPv3, community password change; Secure defaults, Encrypted data at rest, Active FW update, Admin password by default, Cipher & TLS selection; Account lockout; Secure Wi-Fi setup  |
| Country of origin                                    | Made in Vietnam  |

## Learn more at

hp.com

<sup>&</sup>lt;sup>1</sup> For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. <sup>2</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade. <sup>3</sup> Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. Fax capabilities are for sending a fax only, and may require additional purchase. For more information, see: www.hpsmart.com/mobile-4x. <sup>8</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and other warranty. Energy Star value typically based on measurement of T15V device. <sup>8</sup> Begin Electron/mobile and the Blue Angel IEC method with the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is the following possible exceptions: I minute or less sleep delay setting, which is a device or less sleep setting with the following possible exceptions: I minute or less sleep setting with the following possible exceptions: I minute or less sleep setting with the follo

