HP LaserJet MFP M140w Printer



An efficient, high-quality multifunction printer that fits your space and your budget. Get fast printing from HP's smallest laser, plus the time-saving HP Smart app.^{1,2} Count on professional-quality laser printing and seamless setup.





This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

Highlights

- HP's smallest MFP laser in its class
- Print, scan, and copy with one compact device
- Quality and reliability you expect from industry leader
- Print speed up to 20 ppm
- Intuitive, easy to use
- HP Auto-On/Auto-Off technology
- ID copy and icon LCD display

HP's smallest multifunction LaserJet

- Efficient performance from HP's smallest multifunction laser.
- Business doesn't need to wait for your printer. Maximise your uptime with print speeds up to 20 ppm in $A4^{3}$
- Smartly and elegantly designed, so it's simple and intuitive to use.
- Easily handle tasks and get a lot from one device print, scan, and copy.

Productivity from your phone

- Get high-quality scanning, and share to Dropbox, Google Drive or cloud from your phone with HP Smart app.¹
- Access and print documents from your phone with HP Smart app, even from Dropbox and Google Drive.¹
- With HP Smart app, take a photo as a copy, and send it to your printer from your smartphone.¹
- Eliminate steps in repetitive tasks with Shortcuts.¹ Scan to the cloud, email, and more in just a tap.¹

Help save resources without sacrificing performance

- HP Auto-On/Off Technology intelligence can turn your printer on when you need it and off when you
 don't.⁵
- This HP Laser Jet meets ecolabel requirements, including ENERGY STAR[®] and BLUE ANGEL.

Product walkaround

HP LaserJet MFP M140w Printer shown

1. Intuitive control panel

2. World's smallest laser in its class

3. Letter-size flatbed scanner

4. Easy ID copy

Accessories, Supplies and Support

Supplies	W1420A HP 142A Black Original Laser Jet Toner Cartridge (950 pages)
	UG206E HP 3 year Care Pack with Standard Exchange for Laser Jet Printers UG086E HP 3 year Care Pack with Next Day Exchange for Laser Jet Printers UG208E HP 3 year Care Pack with Return to Depot Support for Laser Jet Printers (UG206E: all EMEA countries, except ME, Africa, South Africa, Israel, Turkey, UG086E: Austria, Belgium, Denmark, Finland, France, Germany, Ireland, Italy, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland, UK, Czech, Greece, Hungary, Poland, Slovakia, UG289E: ME, Africa, South Africa, Israel, Turkey)

Technical specifications

reennear specification	
Model	HP LaserJet MFP M140w Printer
Product number	7MD72F
Functions	Print, copy, scan
Control panel	8 buttons (Power, Cancel, Copy, ID Copy, Wireless, Copy setting, Up, Down), 4 LEDs (Ready/Power, Error, Toner, Wireless)
Print	-
Print technology	Laser
Print speed ⁸	Black (A4, normal): Up to 20 ppm
First page out ⁹	Black (A4, ready): As fast as 8.5 sec; Black (A4, sleep): As fast as 9.1 sec
Print resolution	Black (best): Up to 600 x 600 dpi ; Technology: HP FastRes 600
Monthly duty cycle	Up to 8,000 pages A4; Recommended monthly page volume: 100 to 1000
Printer smart software features ^{1,2}	HP Auto-On/Auto-Off ¹ , HP Smart App ²
Standard print languages	PCLm/PCLmS; URF; PWG
Print area	Print margins Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area: 216 x 355.6 mm
Duplex printing	No
Сору	-
Copy speed ¹⁰	Black (A4): Up to 20 cpm
Copier specifications	Number of Copies; Lighter/Darker, Optimize; Paper; Maximum number of copies; Up to 99 copies; Reduce/Enlarge, 25 to 400%
Scan	
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF
	JPG, RAW (bMP), PNG, THP, PDP Scanner type Flatbed; Scan technology. CIS; Scan input modes: Scanning via HP Laser Jet Software Scan or TWAIN-compliant or WIA-compliant software; Twain version: Version 2.1 (Windows 7 or higher); Optical scan resolution: Up to 600
Scanner specifications	Scatter type related, scatted introduced, scatter source and scatter source and the source of the so
Scanner advanced features	No
Recommended monthly scan volume	250 to 2000
Scannable area	Maximum media size (flatbed): 216 to 297 mm
Bit depth/ Grey scale levels	24 bit / 256
Processor speed	500 MHz
Connectivity	
Standard	1 Hi-Speed USB 2.0 (device); Wireless 802.11b/g/n 2.4GHz
Mobile printing capability ⁶	HP Smart App; Apple AirPrint [™] ; Mopria [™] Certified; Wi-Fi® Direct Printing
Supported network protocols	TCP/IP: IPv4; IPv5; IP Direct Mode; LPD; SLP; Bonjour; WS-Discovery; BOTP/DHCP/AutoIP; SNMP v 1/2/3; HTTP/HTTPS; WS Transfer; FQDN; DNS
Memory	Standard: 64 MB ; Maximum: 64 MB Flash ROM: 64 MB DDR1; 32 KB NVRAM
Media handling	אמו שבוב ביו דיים , השוות ביו רים אמות ביו קרווים בסוור, ביום והחופרי
Number of paper trays	Standard: linput tray;Maximum: linput tray
Media types	Para base revelope, postar label
Media size	sum pages to move possible to a state state construction of the state stat
Media handling	Sandard input 150-beta output tay Sandard output 100-beta output and
Media weight	annana angar tao anci angar tao angar angar angar tao angar tao angar ang
Input capacity	Good Loganie Tray 1:Sheets: 150; Envelopes: 10 Maximum: Up to 150 sheets
Output capacity Compatible operating systems	Standard: Up to 100 sheets Ervelopes: Up to 10 ervelopes Maximum: Up to 100 sheets Windows 11; Windows 10; macOS 10.14 Mojave; macOS 10.15 Catalina; macOS 15 Sequoia; Linux
Compatible network operating systems	Windows 11; Windows Server; macOS 15 Sequoia; Linux Windows Microsoft® Windows® 11, 10, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer or Edge.
Minimum system requirements	MacApple [®] macOS called (10.15) macOS Big Sur (11.10) macOS Montex (12.05) Big Sur (11.10) macOS Big Sur (11.10) macOS Big Sur (11.10) macOS Big Sur (11.10) macOS Montex (12.05) Big Sur (11.10) macOS Big Sur (11.1
Software included	No CD in box. Download software from hp.com or 123.hp.com
Security management	Password-protected network embedded Web server; enable/disable Network ports; SNMPv1/2/3 community password change
Printer management	HP Printer Assistant (UDC), HP Device Toolbox
Dimensions and weight	
Printer dimensions (W x D x H)	Minimum 360 x 264 x 197 mm; Maximum 360 x 427 x 347 mm
Printer weight	5.39 kg
Operating environment	Temperature: 15 to 32.5% Humidity: 30 to 70% RH
Storage conditions	Temperature: -20 to 50°C
Acoustics	Acoustic power emissions: 6.2 B(A) Acoustic pressure emissions: 51 dB(A)
	Requirements: 220V - 240V nominal @ +/-10% (min 198V, Max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Typical Electricity Consumption (TEO) ¹¹ : 0.255 kWh/lWeek (Energy Star 3.0); 0.259 kWh/lWeek (Blue Angel); Prover simult have Prever an uniformed ta are based on the nominal relation is off 10 point on parating voltanes. This will damage the printer and which the prever star and the prever star and which the prever sta
Power	Power supply type: Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.
Power Energy savings feature technology Certifications	Requirements: 2207 2409. rominal (#) -/-10%, fmin 1990. Max 26449, 50 - 60/Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Typical Electricity Consumption (TEQ) ¹¹ : 0.255. KWh/Week (Energy Star 3.0); 0.259 KWh/Week (Blue Angel); Power supply type: Power requirements are based on the country/fegion where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RK (Australia), TUV and GS Mark (Germany), BSMI (Taiwan), KC (South Korea), Ukraine, EAC, Estastra Ebased an the country/fegion where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RK (Australia), TUV and GS Mark (Germany), BSMI (Taiwan), KC (South Korea), Ukraine, EAC, Estastra European approvals, CE Marking, FCC, UL, Singapore, etc. Electromagnetic emission Standard: CSPR32:2012 & CISPR32:2015 (FMS5032:2012 & ENS5032:2012 * AuC2016 - Class B; KD 61000-3-2:2014; EN 61000-3-3:2013; EN 55035:2017; FCC Title 47 CFR, Part 15 Class B//CES-003, Issue 6 Ti ECO Declaration: Blue Angel; EPEAT ⁴⁹ Silver distribution when using Original HPS supples Bue Angel compliant Yes, Blue Angel; EPEAT ⁴⁹ Silver distribution when using Original HPS supples Telecom compliance: Wireless: EU RED 2014/53/EU; EN 301 489-17: V3.1.1; EN 300 328: V2.1.1 / EN301 893 V2.1.1; FCC Title 47 CFR, Part 15 Subpart C & E / RSS 247 Issue 1, 2015 & RSS 102 Issue 5, 2015; IEC G2311: 2000
Power Energy savings feature technology	Power supply type. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RCM (Australia), TUV and GS Mark (Germany), BSM (Taiwan), KC (South Korea), Ukraine, EAC, Eastern European approvals, CE Marking, FCC, UL, Singapore, etc. Electromagnetic emission standard: CDSPR32-2012 & CDSPR32-2015 / KC/2015 / KC/2016 /
Power Energy savings feature technology Certifications	Power supply type. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RCM (Australia). TUV and GS Mark (Germany). BSMI (Taiwan). KC (South Korea). Ukraine, EAC, Eastern European approvals, CE Marking, FCC, UL, Singapore, etc. Electromagnetic emission standard: CISPR32:2012 & CISPR32:2012 & ENS5032:2017 + CC 2016 - Class B; EN 651000-3-2:2013; EN 55035:2017; FCC Title 47 CFR, Part 15 Class B/CES-003, Issue 6 If ECO Declarators, Blue Angel; EPEAT [®] Silver ands; EPEAT [®] Silver ands; EPEAT [®] Silver Part Silver Silver Fails Silver (Silver registered in the U.S. Blue Angel compliant Yes, Blue Angel DF-UZ 219—only ensured when using Original HP supplies Telecom compliance: WriteBis: EU RED 2014/53/EU; EN 301 489-1 V2.2.3 / EN 301 489-17: V3.1.1; EN 300 328: V2.1.1 / EN 301 893 V2.1.1; FCC Title 47 CFR, Part 15 Subpart C & E / RSS 247 Issue 1, 2015 & RSS 102 Issue 5, 2015; ECC 62311:2007 / EN62311:2008
Power Energy savings feature technology Certifications Sustainable impact specifications	Power supply type: Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RCM (Austra). TUX and GS Mark (Germany). BSM (Taiwan). KC (South Korea). Ukraine, EAC, Eastern European approvals, CE Marking, FCC, UL, Singapore, etc. Electromagnetic emission standard (CSPR32-2012, & EUSS032-2017; EAC SIDS 5-02-2015; FAC 2016 - Class, ES EN 651000-3-2-2014; EN 15000-3-2-2013; EN 55035-2017; FCC Title 47 CFR, Part 15 Class B/(CES-003, Issue 6 TECD Dataset DE FDR ¹ Silver endice EPAR ¹ Silver endice EPAR ¹ Silver endice EPAR ¹ Silver Part Silver 15; EN 55035-2017; FCC Title 47 CFR, Part 15 Class B/(CES-003, Issue 6 TECD Dataset DE Ide Angel DE-IUZ 219—only ensured when using Drignal HP supplies Telecom compliance Wireless: EUE 2014/53/EU; EN 301 489-1 V2.2.3 (EN 301 489-17; V3.1.1; EN 300 328: V2.1.1 / EN301 893 V2.1.1; FCC Title 47 CFR, Part 15 Subpart C & E / RSS 247 Issue 1, 2015 & RSS 102 Issue 5, 2015; EEC E23 11:2007 / ENG2311:2008 Recyclable through HP Planet Partners; Contains post-consumer recycled plastic
Power Energy savings feature technology Certifications Sustainable impact specifications Country of origin	Power supply type: Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. HP Auto-On/Auto-Off Technology RCM (Austral), TUV and GS Mark (Germany), BSMI (Taiwan), KC (South Korea), Ukraine, EAC, Eastern European approvals, CE Marking, FCC, UL, Singapore, etc. Electromagnetic emission standard: CDSPR32:2015 & (CSPR32:2015 & KCSS032:2017 & ECKSS032:2015 - KC.2016) - 4-2:2014; EN 151000-3-2:2013; EN 55035:2017; FCC Title 47 CFR, Part 15 Class B/CES-003, Issue 6 IT ECO Declaration; Bule Angel, EPAPT % Silver havits laig: EPAPT % Wire varistigie: EPAPT % Silver registered in the U.S. Bue Angel compliant Yes, Blue Angel DE-UZ 219—only ensured when using Original HP supplies Telecom compliance: Wrieless: EU RED 2014/53/EU; EN 301 489-1 V2.2.3 / EN 301 489-17: V3.11; EN 300 328: V2.1.1 / EN301 893 V2.1.1; FCC Title 47 CFR, Part 15 Subpart C& E / RSS 247 Issue 1, 2015 & RSS 102 Issue 5, 2015; IECC 623 11:2007 / ENS23 11:2008 Recyclable through HP Planet Partners; Contains post-consumer recycled plastic Make in Vietnam 7MD72F HP Laser /kt MPP M140w Printer; Power cord; HP Black Laser /kt Toner Cartridge (yield: 300 pages); Setup Poster; Reference Guide; Warranty Guide; Fyer

Footnotes

¹ Smallest in-class footprint compared only to dimensions of majority of personal monochrome laser printers and MFPs. Minimum dimensions used in this analysis. Buyers Lab August 2020 study commissioned by HP, based on a research survey OEM published specifications publicly available information as of 7/31/2020. Per HP, measured footprint for the HP LaserJet Pro M109–112 series is 658.06 square cm (102.0 square inches, and for the HP LaserJet Pro MFP M139–142 series is 949.84 square cm (147.226 square inches). Market share as reported by IDC Quarterly Hardcopy Peripherals Tracker - Final Historical 2020Q1 Worldwide. For details, please see: http://www.keypointintelligence.com/HPSmallestLaser.

² Based on internal HP testing. Average timing estimate based on: 1) downloaded HP Smart app on mobile or desktop device, 2) setting up Shortcut, 3) scanning jobs which have more than 2-3 tasks associated with them (scan to email, save and rename, store to cloud, etc.). Average timing savings comparison based on using printer and desktop scan software to complete similar scanning tasks. Requires the HP Smart app download and supported HP printer. For details on local printing requirements see http://www.hp.com/go/mobileprinting

³ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims . Exact speed varies depending on the system configuration, host OS, port-monitor, software application, driver, and document complexity.

⁴ USB cable not included; purchase separately.

⁵ HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade.

Technical specifications disclaimers

¹ HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade.

² Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. Fax capabilities are for sending a fax only, and may require additional purchase. For more information, see: www.hpsmart.com/mobile-fax

³ For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.

⁴ Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. ⁵ Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. ⁶ Wi-Fi[®] is a registered trademark of Wi-Fi Alliance[®]. Wireless operations are compatible with 2.4 GHz operations only. Learn more at www.hp.com/go/mobileprinting. Wireless performance is dependent upon physical environment and distance from the access point. Air/Print and the Air/Print Logo are trademarks of Apple[®] Inc. The Mopria[®] Logo is a registered and/or unregistered trademark of Mopria Alliance, Inc. in the United States and other countries. Unauthorized use is strictly prohibited. Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mobile applications. Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. Fax capabilities are for sending a fax only, and may require additional purchase. For more information, see: www.hpsmart.com/mobile-fax ⁷ Measured Using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information, see: http://www.hp.com/go/pointerclaims. Exact speed varies depending on the system configuration.

⁷ Measured using ISU/IEL 24734 Feature Performance. Test, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

⁸ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

⁹ Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity

¹⁰ First Copy Out from Ready and Simplex Copy Speed measured using ISO/IEC 29183, Duplex Copy Speed measured using ISO/IEC 24735, excludes first set of test documents. For more information set http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application and document complexity.

¹¹ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device.



© Copyright 2025 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ie-en February 2025

