



## 4 Port USB 2.0 & Audio KM Switch

No.: 32166

Switch between 4 PCs from one keyboard and mouse

### Description

- Controls four PCs using a single keyboard & mouse across four monitors
- Switch via the unit's push buttons, keyboard hot keys and mouse roaming function
- Independent audio switching and 2 ports USB 2.0 Hub for sharing additional USB peripherals
- Plug & Play, no software required
- 2 year warranty

A KM switch allows an operator to conveniently control and manage multiple devices, such as PCs and servers, from a single keyboard and mouse console.

The Lindy 4 Port USB 2.0 & Audio KM Switch is a desktop solution for providing control over four PCs with independent displays from a single keyboard & mouse. Switching between computers can be done by pushing buttons on the front panel of the unit and via keyboard hotkeys; with Mouse Roaming hotkey functions, the user can seamlessly switch between the PCs just by sweeping the mouse cursor across screen borders in different layouts.

The audio output port allow users to connect headphones or speakers to add immersive 2CH audio, while additional USB peripherals can be integrated with the 2 ports USB 2.0 hub. Both audio and USB hub can be switched together with the computers or kept binded to the selected port.

The KM switch can be managed with hotkey switching under every OS without any restrictions. Installation is quick and simple with no software required [BIOS is not supported]. The KM switch can be used with standard wired keyboard & mouse.

Simple to set-up and compatible with a wide range of Lindy USB Extenders, this solution is ideal for small education and business environments, control rooms or for helping make the most of IT equipment in the home.

Please note: wireless devices may not always be recognized.

### Technical details

#### Specifications

- AV Interface: -
- Console Interfaces: USB
- Interface Standard: USB 2.0
- Maximum Resolution: -
- HDCP Support: -

- Supported Audio: Analogue Stereo
- Separate Audio Ports: 3.5mm (Female)
- Serial Interface: -
- Console Number: 1
- Max Number PC/Server: 4
- Cascadable: No
- Switching Method: Push Buttons & Hotkey Switching
- 19" Rack Mountable: -
- Special Features: Mouse Roaming function, Independent audio and USB Hub switching, Active LED Indicators

#### **Connectors**

- Console Interfaces: 2 x USB HID Type A (Female), 3.5mm (Female)
- PC/Server Interfaces: 4 x USB 2.0 Type B (Female), 4 x 3.5mm (Female)
- Other Interfaces: 2 x USB 2.0 Type A (Female)
- Power: 5.5/2.1mm DC socket

#### **Physical Properties**

- Dimensions WxDxH: 220x100x34mm [8.66x3.94x1.34in]
- Housing Material: Metal
- Net Weight: 0.85kg [1.87lb]
- Operating Temperature: 0°C - 45°C [32°F - 113°F]
- Storage Temperature: -20°C - 60°C [-4°F - 140°F]
- Humidity: 0~90% RH (non-condensing)
- Power Requirements: 12VDC 1.5A
- Colour: Black

#### **Miscellaneous**

- Packaging Type: Carton box
- Packaging Dimensions: 295x210x65mm [11.61x8.27x2.56in]
- Gross Weight: 1.14kg [2.51lb]
- Warranty (Years): 2
- Certificated: CE, UKCA, FCC, RoHS, REACH & California Proposition 65

#### **Package Contents**

- KM Switch
- Multi-Country Power Supply (UK, EU, US, AUS)
- 4 x Rubber Feet
- Lindy Manual

#### **Purchasing Information**

- No.: 32166
- EAN: 4002888321662